

What is claimed is:

1. A disk drive comprising:

actuator means for positioning a head relative to a disk;

driving means for driving the actuator means;

5 voltage detection means for detecting a voltage generated when driving the actuator means, and for outputting a voltage signal;

disturbance estimation means for estimating a magnitude of a disturbance applied to the head from a driving signal for the driving means and the voltage signal, and for generating
10 a disturbance estimation signal;

position detection means for generating a position error signal corresponding to a current position of the head from servo information recorded on the disk in advance and detected by the
15 head;

position control means for generating a position control means corresponding to the position error signal; and

correction means for combining the position control signal with the disturbance estimation signal to obtain the driving
20 signal, wherein

the disturbance estimation means comprises:

comparison means for comparing the disturbance estimation signal generated by the disturbance estimation means with the voltage signal, and for outputting a deviation signal; and

25 addition means for adding a signal obtained by multiplying an integral signal, obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying a proportional signal proportional to the deviation signal by a second coefficient, and for generating the disturbance
30 estimation signal.

2. The disk drive according to claim 1, wherein the disturbance estimation means comprises:

comparison means which inputs the voltage signal detected by the voltage detection means;

first multiplication means for multiplying the driving signal by a coefficient consisting of a first transfer function;

5 second multiplication means for multiplying an output of the comparison means by a coefficient consisting of a second transfer function;

first integral means for integrating the output of the comparison means; and

10 second integral means for integrating a value obtained by subtracting an addition value, obtained by adding an output of the second multiplication means and an output of the first integral means, from an output of the first multiplication means, and wherein

15 the comparison means compares an output of the second integral means with the voltage signal, and outputs a difference between the output of the second integral means and the voltage signal to the second multiplication means and the first integral means.

20

3. The disk drive according to claim 1, wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2 - \omega_d^2)$, where ω_0 is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

25

4. The disk drive according to claim 1, wherein

a control band of the disturbance estimation means is set wider than a control band of the position control means.

30

5. A disk drive comprising:

actuator means for positioning a head relative to a disk;

driving means for driving the actuator means;

voltage detection means for detecting a voltage generated when driving the actuator means, and for outputting a voltage signal;

5 disturbance estimation means for estimating a magnitude of a disturbance applied to the head from a driving signal for the driving means and the voltage signal, and for generating a disturbance estimation signal;

10 position detection means for generating a position error signal corresponding to a current position of the head from servo information recorded on the disk in advance and detected by the head;

position control means for generating a position control means corresponding to the position error signal; and

15 correction means for combining the position control signal with the disturbance estimation signal to generate the driving signal, wherein

the disturbance estimation means comprises:

20 comparison means for comparing the disturbance estimation signal generated by the disturbance estimation means with the voltage signal, and for outputting a deviation signal;

filter means for cutting off a high frequency component of a proportional signal proportional to the deviation signal, and for generating a filter output signal; and

25 addition means for adding a signal obtained by multiplying an integral signal, obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying the filter output signal by a second coefficient, and for generating the disturbance estimation signal.

30 6. The disk drive according to claim 5, wherein

the disturbance estimation means comprises:

comparison means which inputs the voltage signal detected by the voltage detection means;

first multiplication means for multiplying the driving signal by a coefficient consisting of a first transfer function;

second multiplication means for multiplying an output of the comparison means by a coefficient consisting of a second transfer function;

first integral means for integrating the output of the comparison means; and

second integral means for integrating a value obtained by subtracting an addition value, obtained by adding an output of the second multiplication means and an output of the first integral means, from an output of the first multiplication means, and wherein

the comparison means compares an output of the second integral means with the voltage signal, and outputs a difference between the output of the second integral means and the voltage signal to the second multiplication means and the first integral means.

7. The disk drive according to claim 5, wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_o^2/(\omega_o^2 - \omega_d^2)$, where ω_o is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

8. The disk drive according to claim 5, wherein

a control band of the disturbance estimation means is set wider than a control band of the position control means.

9. A disk drive comprising:

actuator means for positioning a head relative to a disk;
driving means for driving the actuator means;
voltage detection means for detecting a voltage generated when driving the actuator means, and for outputting a voltage

signal;

position detection means for generating a position error signal corresponding to a current position of the head from servo information recorded on the disk in advance and detected by the head;

position control means for generating a position control means corresponding to the position error signal;

disturbance estimation means for estimating a magnitude of a disturbance applied to the head from the position control signal and the voltage signal, and for generating a disturbance estimation signal;

correction means for combining the position control signal with the disturbance estimation signal to generate the driving signal, wherein

the disturbance estimation means comprises:

comparison means for comparing the disturbance estimation signal generated by the disturbance estimation means with the voltage signal, and for outputting a deviation signal; and

addition means for adding a signal obtained by multiplying an integral signal, obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying a proportional signal proportional to the deviation signal by a second coefficient, and for generating the disturbance estimation signal.

10. The disk drive according to claim 9, wherein the disturbance estimation means comprises:

comparison means which inputs the voltage signal detected by the voltage detection means;

first multiplication means for multiplying the position control signal by a coefficient consisting of a first transfer function;

second multiplication means for multiplying an output of

the comparison means by a coefficient consisting of a second transfer function;

first integral means for integrating the output of the comparison means; and

5 second integral means for integrating a value obtained by subtracting an addition value, obtained by adding an output of the second multiplication means and an output of the first integral means, from an output of the first multiplication means, and wherein

10 the comparison means compares an output of the second integral means with the voltage signal, and outputs a difference between the output of the second integral means and the voltage signal to the second multiplication means and the first integral means.

15

11. The disk drive according to any one of claims 1 to 9, wherein a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_o^2/(\omega_o^2 - \omega_d^2)$, where ω_o is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

20

12. The disk drive according to claim 9, wherein the first coefficient is set at 1.

25

13. The disk drive according to claim 9, wherein a control band of the disturbance estimation means is set wider than a control band of the position control means.

14. A disk drive comprising:

30

actuator means for positioning a head relative to a disk;
driving means for driving the actuator means;
voltage detection means for detecting a voltage generated when driving the actuator means, and for outputting a voltage

signal;

position detection means for generating a position error signal corresponding to a current position of the head from servo information recorded on the disk in advance and detected by the head;

position control means for generating a position control means corresponding to the position error signal;

disturbance estimation means for estimating a magnitude of a disturbance applied to the head from the position control signal and the voltage signal, and for generating a disturbance estimation signal;

correction means for combining the position control signal with the disturbance estimation signal to generate the driving signal, wherein

the disturbance estimation means comprises:

comparison means for comparing the disturbance estimation signal generated by the disturbance estimation means with the voltage signal, and for outputting a deviation signal;

filter means for cutting off a high frequency component of a proportional signal proportional to the deviation signal, and for generating a filter output signal; and

addition means for adding a signal obtained by multiplying an integral signal, which is obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying the filter output signal by a second coefficient, and for generating the disturbance estimation signal.

15. The disk drive according to claim 14, wherein the disturbance estimation means comprises:

comparison means which inputs the voltage signal detected by the voltage detection means;

first multiplication means for multiplying the position control signal by a coefficient consisting of a first transfer

function;

second multiplication means for multiplying an output of the comparison means by a coefficient consisting of a second transfer function;

5 first integral means for integrating the output of the comparison means; and

second integral means for integrating a value obtained by subtracting an addition value, obtained by adding an output of the second multiplication means and an output of the first
10 integral means, from an output of the first multiplication means, and wherein

the comparison means compares an output of the second integral means with the voltage signal, and outputs a difference between the output of the second integral means and the voltage
15 signal to the second multiplication means and the first integral means.

16. The disk drive according to claim 14, wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second
20 coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2 - \omega_d^2)$, where ω_0 is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

17. The disk drive according to claim 14, wherein

25 the first coefficient is set at 1.

18. The disk drive according to claim 14, wherein

a control band of the disturbance estimation means is set wider than a control band of the position control means.

30

19. A disk drive control method comprising the steps of:

generating a position error signal corresponding to a current position of a head from servo information recorded on

a disk in advance and detected by the head;

generating a position control signal corresponding to the position error signal;

5 generating a voltage estimation signal that is an estimate of a voltage signal, which is generated when driving actuator means for positioning the head, based on a driving signal for the actuator means and the voltage signal;

10 comparing the voltage estimation signal with the voltage signal, and generating a deviation signal which indicates a difference between the voltage estimation signal and the voltage signal;

15 adding a signal obtained by multiplying an integral signal, which is obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying a proportional signal proportional to the deviation signal by a second coefficient, and thereby generating a disturbance estimation signal;

20 combining the position control signal and the disturbance estimation signal, and generating the driving signal; and driving the actuator means by the driving signal, and positioning the head relative to the disk.

20. The disk drive control method according to claim 19, wherein

25 a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2 - \omega_d^2)$, where ω_0 is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

30 21. The disk drive control method according to claim 19, wherein

a control band of the disturbance estimation is set wider than a control band of the position control.

22. A disk drive control method comprising the steps of:
generating a position error signal corresponding to a
current position of a head from servo information recorded on
5 a disk in advance and detected by the head;
generating a position control signal corresponding to the
position error signal;
generating a voltage estimation signal that is an estimate
of a voltage signal, which is generated when driving actuator
10 means for positioning the head, based on a driving signal for
the actuator means and the voltage signal;
comparing the voltage estimation signal with the voltage
signal, and generating a deviation signal which indicates a
difference between the voltage estimation signal and the voltage
15 signal;
adding a signal obtained by multiplying an integral signal,
which is obtained by integrating the deviation signal, by a first
coefficient and a filter output signal obtained by cutting off
a high frequency component of a proportional signal proportional
20 to the deviation signal by a second coefficient, and thereby
generating a disturbance estimation signal;
combining the position control signal and the disturbance
estimation signal, and generating the driving signal; and
driving the actuator means by the driving signal, and
25 positioning the head relative to the disk.

23. The disk drive control method according to claim 22,
wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second
30 coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2 - \omega_d^2)$,
where ω_0 is an estimation frequency of the disturbance estimation
means and ω_d is a disturbance frequency.

24. The disk drive control method according to claim 22, wherein

a control band of the disturbance estimation is set wider than a control band of the position control.

5

25. A disk drive control method comprising the steps of:

generating a position error signal corresponding to a current position of a head from servo information recorded on a disk in advance and detected by the head;

10 generating a position control signal corresponding to the position error signal;

generating a voltage estimation signal that is an estimate of a voltage signal, which is generated when driving actuator means, based on the position control signal and the voltage signal;

15

comparing the voltage estimation signal with the voltage signal, and generating a deviation signal which indicates a difference between the voltage estimation signal and the voltage signal;

20

adding a signal obtained by multiplying an integral signal, which is obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying a proportional signal proportional to the deviation signal by a second coefficient, and thereby generating a disturbance estimation signal;

25

combining the position control signal and the disturbance estimation signal, and generating the driving signal; and driving the actuator means by the driving signal, and positioning the head relative to the disk.

30

26. The disk drive control method according to claim 25, wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second

coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2-\omega_d^2)$, where ω_0 is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

5 27. The disk drive control method according to claim 25, wherein

the first coefficient is set at 1.

28. The disk drive control method according to claim 25,
10 wherein

a control band of the disturbance estimation is set wider than a control band of the position control.

29. A disk drive control method comprising the steps of:
15 generating a position error signal corresponding to a current position of a head from servo information recorded on a disk in advance and detected by the head;

generating a position control signal corresponding to the position error signal;

20 generating a voltage estimation signal that is an estimate of a voltage signal, which is generated when driving actuator means, based on the position control signal and the voltage signal;

25 comparing the voltage estimation signal with the voltage signal, and generating a deviation signal which indicates a difference between the voltage estimation signal and the voltage signal;

30 adding a signal obtained by multiplying an integral signal, which is obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying a filter output signal obtained by cutting off a high frequency component of a proportional signal proportional to the deviation signal by a second coefficient, and thereby generating a disturbance

estimation signal;

combining the position control signal and the disturbance estimation signal, and generating the driving signal; and

driving the actuator means by the driving signal, and
5 positioning the head relative to the disk.

30. The disk drive control method according to claim 29, wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second
10 coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2 - \omega_d^2)$,
where ω_0 is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

31. The disk drive control method according to claim 29,
15 wherein

the first coefficient is set at 1.

32. The disk drive control method according to claim 29, wherein

20 a control band of the disturbance estimation is set wider
than a control band of the position control.

33. A disk drive comprising:

actuator means for loading and unloading a head to and
25 from a disk;

driving means for driving the actuator means;

voltage detection means for detecting a voltage generated
when driving the actuator means, and for outputting a voltage
signal;

30 disturbance estimation means for estimating a magnitude
of a disturbance applied to the head from a driving signal for
the driving means and the voltage signal, and for generating
a disturbance estimation signal;

velocity control means for generating a velocity control signal from a velocity instruction signal and the voltage signal; and

5 correction means for combining the velocity control signal and the disturbance estimation signal, and for thereby generating the driving signal, wherein

the disturbance estimation means comprises:

comparison means for comparing the disturbance estimation signal generated by the disturbance estimation means with the voltage signal, and for outputting a deviation signal; and

10 addition means for adding a signal obtained by multiplying an integral signal, which is obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying a proportional signal proportional to the deviation signal by a second coefficient, and for generating

15 the disturbance estimation signal.

34. The disk drive according to claim 33, wherein

the disturbance estimation means comprises:

20 comparison means which inputs the voltage signal output from the voltage detection means;

first multiplication means for multiplying the driving signal by a coefficient consisting of a first transfer function;

second multiplication means for multiplying an output of the comparison means by a coefficient consisting of a second transfer function;

25 first integral means for integrating the output of the comparison means; and

second integral means for integrating a value obtained by subtracting an addition value, which is obtained by adding an output of the second multiplication means and an output of the first integral means, from an output of the first multiplication means, and wherein

30

the comparison means compares an output of the second integral means with the voltage signal, and outputs a difference between the output of the second integral means and the voltage signal to the second multiplication means and the first integral means.

35. The disk drive according to claim 33, wherein a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_o^2/(\omega_o^2 - \omega_d^2)$, where ω_o is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

36. The disk drive according to claim 33, wherein the velocity control means generates the velocity control means from the velocity instruction signal and a velocity estimation signal generated by the disturbance estimation means.

37. The disk drive according to claim 33, wherein a control band of the disturbance estimation means is set wider than a control band of the velocity control means.

38. A disk drive comprising:
actuator means for loading and unloading a head to and from a disk;
driving means for driving the actuator means;
voltage detection means for detecting a voltage generated when driving the actuator means, and for outputting a voltage signal;

disturbance estimation means for estimating a magnitude of a disturbance applied to the head from a driving signal for the driving means and the voltage signal, and for generating a disturbance estimation signal;

velocity control means for generating a velocity control

signal from a velocity instruction signal and the voltage signal;
and

correction means for combining the velocity control signal
and the disturbance estimation signal, and for thereby generating
5 the driving signal, wherein

the disturbance estimation means comprises:

comparison means for comparing the disturbance estimation
signal generated by the disturbance estimation means with the
voltage signal, and for outputting a deviation signal;

10 filter means for cutting off a high frequency component
of a proportional signal proportional to the deviation signal,
and for generating a filter output signal; and

addition means for adding a signal obtained by multiplying
an integral signal, which is obtained by integrating the
deviation signal, by a first coefficient and a signal obtained
15 by multiplying the filter output signal by a second coefficient,
and for generating the disturbance estimation signal.

39. The disk drive according to claim 38, wherein

20 the disturbance estimation means comprises:

comparison means which inputs the voltage signal detected
by the voltage detection means;

first multiplication means for multiplying the driving
signal by a coefficient consisting of a first transfer function;

25 second multiplication means for multiplying an output of
the comparison means by a coefficient consisting of a second
transfer function;

first integral means for integrating the output of the
comparison means; and

30 second integral means for integrating a value obtained
by subtracting an addition value, which is obtained by adding
an output of the second multiplication means and an output of
the first integral means, from an output of the first

multiplication means, and wherein

the comparison means compares an output of the second integral means with the voltage signal, and outputs a difference between the output of the second integral means and the voltage
5 signal to the second multiplication means and the first integral means.

40. The disk drive according to claim 38, wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second
10 coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2 - \omega_d^2)$, where ω_0 is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

41. The disk drive according to claim 38, wherein

15 the velocity control means generates the velocity control means from the velocity instruction signal and a velocity estimation signal generated by the disturbance estimation means.

42. The disk drive according to claim 38, wherein

20 a control band of the disturbance estimation means is set wider than a control band of the velocity control means.

43. A disk drive comprising:

25 actuator means for loading and unloading a head to and from a disk;

driving means for driving the actuator means;

voltage detection means for detecting a voltage generated when driving the actuator means, and for outputting a voltage
signal;

30 disturbance estimation means for estimating a magnitude of a disturbance applied to the head from a velocity control signal and the voltage signal, and for generating a disturbance estimation signal;

velocity control means for generating a velocity control signal from a velocity instruction signal and the voltage signal; and

5 correction means for combining the velocity control signal and the disturbance estimation signal, and for thereby generating the driving signal, wherein

the disturbance estimation means comprises:

10 comparison means for comparing the disturbance estimation signal generated by the disturbance estimation means with the voltage signal, and for outputting a deviation signal; and

addition means for adding a signal obtained by multiplying an integral signal, which is obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying a proportional signal proportional to the deviation signal by a second coefficient, and for generating
15 the disturbance estimation signal.

44. The disk drive according to claim 43, wherein

the disturbance estimation means comprises:

20 comparison means which inputs the voltage signal detected by the voltage detection means;

first multiplication means for multiplying the position control signal by a coefficient consisting of a first transfer function;

25 second multiplication means for multiplying an output of the comparison means by a coefficient consisting of a second transfer function;

first integral means for integrating the output of the comparison means; and

30 second integral means for integrating a value obtained by subtracting an addition value, which is obtained by adding an output of the second multiplication means and an output of the first integral means, from an output of the first

multiplication means, and wherein

the comparison means compares an output of the second integral means with the voltage signal, and outputs a difference between the output of the second integral means and the voltage signal to the second multiplication means and the first integral means.

45. The disk drive according to claim 43, wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_o^2/(\omega_o^2 - \omega_d^2)$, where ω_o is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

46. The disk drive according to claim 43, wherein

the first coefficient is set at 1.

47. The disk drive according to claim 43, wherein

the velocity control means generates the velocity control means from the velocity instruction signal and a velocity estimation signal generated by the disturbance estimation means.

48. The disk drive according to claim 43, wherein

a control band of the disturbance estimation means is set wider than a control band of the velocity control means.

49. A disk drive comprising:

actuator means for loading and unloading a head to and from a disk;

driving means for driving the actuator means;

voltage detection means for detecting a voltage generated when driving the actuator means, and for outputting a voltage signal;

disturbance estimation means for estimating a magnitude

of a disturbance applied to the head from a velocity control signal and the voltage signal, and for generating a disturbance estimation signal;

velocity control means for generating a velocity control
5 signal from a velocity instruction signal and the voltage signal;
and

correction means for combining the velocity control signal
and the disturbance estimation signal, and for thereby generating
the driving signal, wherein

10 the disturbance estimation means comprises:

comparison means for comparing the disturbance estimation
signal generated by the disturbance estimation means with the
voltage signal, and for outputting a deviation signal;

filter means for cutting off a high frequency component
15 of a proportional signal proportional to the deviation signal,
and for generating a filter output signal; and

addition means for adding a signal obtained by multiplying
an integral signal, which is obtained by integrating the
deviation signal, by a first coefficient and a signal obtained
20 by multiplying the filter output signal by a second coefficient,
and for generating the disturbance estimation signal.

50. The disk drive according to claim 49, wherein

the disturbance estimation means comprises:

25 comparison means which inputs the voltage signal output
from the voltage detection means;

first multiplication means for multiplying the position
control signal by a coefficient consisting of a first transfer
function;

30 second multiplication means for multiplying an output of
the comparison means by a coefficient consisting of a second
transfer function;

first integral means for integrating the output of the

comparison means; and

second integral means for integrating a value obtained by subtracting an addition value, which is obtained by adding an output of the second multiplication means and an output of the first integral means, from an output of the first multiplication means, and wherein

the comparison means compares an output of the second integral means with the voltage signal, and outputs a difference between the output of the second integral means and the voltage signal to the second multiplication means and the first integral means.

51. The disk drive according to claim 49, wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2-\omega_d^2)$, where ω_0 is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

52. The disk drive according to claim 49, wherein

the first coefficient is set at 1.

53. The disk drive according to claim 49, wherein

the velocity control means generates the velocity control means from the velocity instruction signal and a velocity estimation signal generated by the disturbance estimation means.

54. The disk drive according to claim 49, wherein

a control band of the disturbance estimation means is set wider than a control band of the velocity control means.

55. A disk drive control method comprising the steps of:

generating a velocity control signal corresponding to a velocity instruction;

generating a voltage estimation signal that is an estimate of a voltage signal, which is generated when driving actuator means for loading and unloading a head, based on a driving signal for the actuator means and the voltage signal;

5 comparing the voltage estimation signal with the voltage signal, and generating a deviation signal which indicates a difference between the voltage estimation signal and the voltage signal;

10 adding a signal obtained by multiplying an integral signal, which is obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying a proportional signal proportional to the deviation signal by a second coefficient, and thereby generating a disturbance estimation signal;

15 combining the velocity control signal and the disturbance estimation signal, and generating the driving signal; and
 driving the actuator means by the driving signal, and loading and unloading the head to and from the disk.

20 56. The disk drive control method according to claim 55, wherein

 a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2 - \omega_d^2)$, where ω_0 is an estimation frequency of the disturbance estimation
25 means and ω_d is a disturbance frequency.

57. The disk drive control method according to claim 55, wherein

30 a control band of the disturbance estimation is set wider than a control band of the position control.

58. A disk drive control method comprising the steps of:
 generating a velocity control signal corresponding to a

velocity instruction;

generating a voltage estimation signal that is an estimate of a voltage signal, which is generated when driving actuator means for loading and unloading a head, based on a driving signal
5 for the actuator means and the voltage signal;

comparing the voltage estimation signal with the voltage signal, and generating a deviation signal which indicates a difference between the voltage estimation signal and the voltage signal;

10 adding a signal obtained by multiplying an integral signal, which is obtained by integrating the deviation signal, by a first coefficient and a filter output signal obtained by cutting of a high frequency component of a proportional signal proportional to the deviation signal by a second coefficient, and thereby
15 generating a disturbance estimation signal;

combining the velocity control signal and the disturbance estimation signal, and generating the driving signal; and

driving the actuator means by the driving signal, and loading and unloading the head to and from the disk.

20

59. The disk drive control method according to claim 58, wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_o^2/(\omega_o^2 - \omega_d^2)$,
25 where ω_o is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

60. The disk drive control method according to claim 58, wherein

30 a control band of the disturbance estimation is set wider than a control band of the position control.

61. A disk drive control method comprising the steps of:

generating a velocity control signal corresponding to a velocity instruction;

generating a voltage estimation signal that is an estimate of a voltage signal, which is generated when driving actuator means, based on the velocity control signal and the voltage signal;

comparing the voltage estimation signal with the voltage signal, and generating a deviation signal which indicates a difference between the voltage estimation signal and the voltage signal;

adding a signal obtained by multiplying an integral signal, which is obtained by integrating the deviation signal, by a first coefficient and a signal obtained by multiplying a proportional signal proportional to the deviation signal by a second coefficient, and thereby generating a disturbance estimation signal;

combining the velocity control signal and the disturbance estimation signal, and generating the driving signal; and

driving the actuator means by the driving signal, and loading and unloading the head to and from the disk.

62. The disk drive control method according to claim 61, wherein

a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2 - \omega_d^2)$, where ω_0 is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

63. The disk drive control method according to claim 61, wherein

the first coefficient is set at 1.

64. The disk drive control method according to claim 61,

wherein

a control band of the disturbance estimation is set wider than a control band of the position control.

- 5 65. A disk drive control method comprising the steps of:
generating a velocity control signal corresponding to a velocity instruction;
generating a voltage estimation signal that is an estimate of a voltage signal, which is generated when driving actuator means for loading and unloading a head, based on the velocity control signal and the voltage signal;
10 comparing the voltage estimation signal with the voltage signal, and generating a deviation signal which indicates a difference between the voltage estimation signal and the voltage signal;
15 adding a signal obtained by multiplying an integral signal, which is obtained by integrating the deviation signal, by a first coefficient and a filter output signal obtained by cutting off a high frequency component of a proportional signal proportional to the deviation signal by a second coefficient, and thereby generating a disturbance estimation signal;
20 combining the velocity control signal and the disturbance estimation signal, and generating the driving signal; and
driving the actuator means by the driving signal, and
25 loading and unloading the head to and from the disk.

66. The disk drive control method according to claim 65, wherein

- 30 a ratio k_2/k_1 of the first coefficient k_1 and the second coefficient k_2 is set to substantially satisfy $\omega_0^2/(\omega_0^2 - \omega_d^2)$, where ω_0 is an estimation frequency of the disturbance estimation means and ω_d is a disturbance frequency.

67. The disk drive control method according to claim 65,
wherein

the first coefficient is set at 1.

5 68. The disk drive control method according to claim 65,
wherein

a control band of the disturbance estimation is set wider
than a control band of the position control.

10